

Home Phone Configuration Settings for BYO Modem

These are the settings that you need to set up your Home Phone service using your own modem. The setup on each device varies so some items might not be applicable.

If you're using a SpinTel provided modem you won't need to configure the phone service. The network will automatically update the settings.

SIP Username: *The username provided by SpinTel*

SIP Password: *The password provided by SpinTel*

Telephone Number: *Same as SIP Username*

Line Number: *Same as SIP Username*

SIP Server: 203.23.236.96

Registrar Address: 203.23.236.96

Outbound Proxy: 203.23.236.96

User Domain: 203.23.236.96

Preferred Codec: G.729

Silence Suppression: Disable

Echo Cancellation: Enabled

STUN Server: Off

SIP Expire Time: 3600

Default SIP Port: 5060

DSCP Masking: Premium

Note: Other devices may ask for details such as **Authentication Number** or **other numbers**. Always use your **SIP Username** and **NOT** your telephone number.

Online URL:

<https://articles.spintel.net.au/article/home-phone-configuration-settings-for-byo-modem.html>